

KAM

INSTRUCTION MANUAL



For information on the entire Kam range and all the latest new products visit:

www.kam.co.uk

Kam products are manufactured by: **Lamba plc**, Unit 1, Southfields Road, Dunstable, Bedfordshire, United Kingdom LU6 3EJ
Telephone: (+44) (0)1582 690600 • Fax: (+44) (0)1582 690400 • Email: mail@lambapl.com • Web: www.lambapl.com

KAM DMX1500 STROBE

Full DMX controlled strobe with up to 20 flashes per second

www.kam.co.uk

KAM DMX1500 STROBE

Full DMX controlled strobe with up to 20 flashes per second

INTRODUCTION

Thank you for purchasing the Kam DMX1500W Strobe.

To optimize the performance of this product, prior to use, please read these operating instructions carefully to familiarize yourself with the basic operations of this unit. Keep these user instructions in safe place for future reference.

This unit has been tested at the factory before being shipped to you. There is no assembly required.

PACKAGING

Please unpack your new strobe effect carefully, making sure there is not damage to the unit that may have been caused in transit. If any damage is found DO NOT use the strobe unit or connect it to the mains. Contact the retailer that you purchased the strobe from immediately.

FEATURES

1500W ultra bright strobe tube
Full DMX 512 control
Operates on 2 DMX channels
1-20 flashes per second
Infinite dimmer control variable from 0-100%
10 million flash lamp life
Built in sound activation mode
Adjustable flash rate in standalone mode via dip switches
Adjustable hanging bracket
Black metal chassis

USING THE DIP SWITCHES TO MANUALLY OPERATE THE STROBE WITHOUT A DMX CONTROLLER

Dip switch setting and function

ON	OFF	FUNCTION
10, 1	2, 3, 4, 5, 6, 7, 8, 9	Slow strobe, 4 flashes / per sec
10, 2	1, 3, 4, 5, 6, 7, 8, 9	Middle strobe, 9 flashes / per sec
10, 3	1, 2, 4, 5, 6, 7, 8, 9	Fast strobe, 16 flashes / per sec
10, 4	1, 2, 3, 5, 6, 7, 8, 9	Strobe dim 30%
10, 5	1, 2, 3, 4, 6, 7, 8, 9	Strobe dim 50%
10, 6	1, 2, 3, 4, 5, 7, 8, 9	Strobe 100%

PRODUCT FEATURES KEY

1. Mains lead input
2. Fuse holder
3. DMX address dip switches
4. DMX out socket
5. DMX input socket

SPECIFICATION

Power voltage: 220/240V AC 50Hz

Lamp power: 1510W

Dimensions: 460 x 210 x 138mm

Weight: 3.6Kg

WARNING

This unit can get hot after prolonged use, please allow 15 minutes of cooling down time before carrying out any servicing, cleaning, or moving of the equipment. Do not allow any of the cooling vents to be blocked on this unit. This strobe is for indoor use only and must not be exposed to rain or moisture. Do not place this unit on or next to any flammable materials. Disconnect from the mains before carrying out and cleaning or maintenance.

USAGE

Please check with your venue or local authority for regulations of usage of your strobe effect units.

