



|    |   |   |  |
|----|---|---|--|
| 13 | 4 | 128-135 Macro 16<br>136-143 Macro 17<br>144-151 Macro 18<br>152-159 Macro 19<br>160-167 Macro 20<br>168-175 Macro 21<br>176-183 Macro 22<br>184-191 Macro 23<br>192-199 Macro 24<br>200-207 Macro 25<br>208-215 Macro 26<br>216-223 Macro 27<br>224-231 Macro 28<br>232-239 Macro 29<br>240-247 Macro 30<br>248-255 Macro 31-rainbow effect from slow to fast | step<br>step<br>step<br>step<br>step<br>step<br>step<br>step<br>step<br>step<br>step<br>step<br>step<br>step<br>step<br>step<br>step<br>proportional |
| 14 | 5 | <b>SHUTTER/STROBE</b><br>0-31 Shutter closed<br>32-63 Shutter open<br>64-95 Strobe-effect from slow to fast<br>96-127 Shutter open<br>128-143 Opening pulses in sequences from slow to fast<br>144-159 Closing pulses in sequences from fast to slow<br>160-191 Shutter open<br>192-223 Random strobe-effects from slow to fast<br>224-255 Shutter open       | step<br>step<br>proportional<br>step<br>proportional<br>proportional<br>step<br>proportional<br>step   |
| 15 | 6 | <b>DIMMER</b><br>0-255 Dimmer intensity from 0% to 100%   | proportional   |

**Zone positions:**  
(every zone contains two LED modules)

